



# SR MINI INTIMIDATOR

Variable-output side-switch LED flashlight

MAX	TOTAL	BATTERY	WATERPROOF
			
2800 LUMENS	16 HOURS	CR123A X 6 OR 18650 X 3	2M [IPX8]



## FEATURES

- A highly diffused acrylic lens emits a smooth floodlight for soft area lighting
- Side switch cycles through three brightness levels, activates strobe and momentary turbo mode
- The side switch illuminates to notify a user when the flashlight is on to avoid over-heating and save battery life if the head is down
- From the off position, automatically return to your last brightness level with the built-in memory function
- Waterproof up to 2 meters
- Aircraft-grade aluminum body with anti-scratch type III hard anodizing
- Compatible with CR123A and 18650 batteries

All tests are carried out consistent to ANSI standard testing with 3 x 18650 3.6V 3400mAh batteries.

# SR MINI INTIMIDATOR

Variable-output side-switch LED flashlight

Specifications



Note: testing done with 3 x 18650 3.6V  
3400mAh batteries

	MODE 1	MODE 2	MODE 3	MODE 4
	<b>2800</b> LUMENS	<b>1200</b> LUMENS	<b>600</b> LUMENS	<b>200</b> LUMENS
	<b>2</b> HRS	<b>3.5</b> HRS	<b>7</b> HRS	<b>16</b> HRS
	<b>224 METERS</b>			
	<b>12,600 CD</b>			
	<b>2 METERS</b>			
	<b>1.5 METERS</b>			
	<b>3 x CREE XM-L2 CW LED</b>			
	<b>6 x CR123A or 3 x 18650</b>			
	<b>127mm (L) x 48mm (D) / 5.0 in x 1.9 in</b>			
	<b>286g / 10.1 oz</b>			

# SR MINI INTIMIDATOR

Variable-output side-switch LED flashlight

## Switch Operation

1. **ON/OFF:** Click the side switch. The flashlight will return to the last used brightness level.
2. **STROBE:** Click the side switch three times when the light is on or off.
3. **TURBO:** Press and hold the side switch. Turbo mode is only active while switch is depressed for momentary on. Release the side switch to return to last used mode.

## Change Brightness Level:

When light is on, quickly click the side switch twice to change brightness levels. The brightness levels will cycle up to high then start again at the low setting.



# SR MINI INTIMIDATOR

Variable-output side-switch LED flashlight

QUALITY

5

YEAR  
WARRANTY

PROMISE



## OUR WARRANTY

Here at Olight, we believe in our products. If your Olight product has any defects as the result of the materials or workmanship, we want to make it right! Within 30 days of purchase, return the product to the retailer you purchased from and they will replace or repair it. Period. Within 5 years of your purchase, return the product to Olight and we will repair or replace it. End of story.

After 5 years of purchase, return the product to Olight and we will repair or replace the product. You just pay for the parts. Of course, this warranty does not cover normal wear and tear. This warranty also does NOT cover modifications, misuse, disintegrations, negligence, accidents, improper maintenance, or repair by anyone other than an Authorized Retailer or Olight itself. Buyer is responsible for shipping costs of returned products.